

# ACCESSORY PRODUCT DATA SHEET

Part #: 60012



## SAYLOR MOBILE POWER PANELS

<b>CONTRACTOR NAME:</b>	Celina Tent Inc. (CELINA)												
<b>MANUFACTURING SOURCE COMPANY:</b>	Celina Tent Inc. (CELINA)												
<b>PART NUMBER OR NSN:</b>	60012												
<b>SPECIFICATIONS AS APPLICABLE:</b>	CELINA Shelters												
<b>ITEM TYPE:</b>	Mobile power distribution panels												
<b>AMP RATING:</b>	200 amp, 3-phase panels main safety fusible disconnect switch, 42 electrical circuits per panel												
<b>VOLT RATING:</b>	Voltage rating to be 120/208 or 120/240 or 277/480												
<b>WEIGHT (UNPACKAGED) (LB):</b>	680 lb												
<b>SPECIAL/ADDITIONAL FEATURES:</b>	<ul style="list-style-type: none"> <li>• Measurements: 6' 5" height x 58" length x 3' 6" width</li> <li>• Each unit has a 5 color coded single-pole Cam-Lok male plugs with 3/0 wire for quick and easy generator connection</li> <li>• Optional GFCI main circuit breaker for full panel surge protection</li> <li>• Meets all NEC Code requirements and is NEMA 3 rated for indoor/outdoor use</li> <li>• Completely mobile with locking wheels</li> </ul> <table border="1" style="width: 100%; margin-top: 10px;"> <thead> <tr> <th style="width: 50%;">Panel (A)</th> <th style="width: 50%;">Panel (B)</th> </tr> </thead> <tbody> <tr> <td>(4 or more circuits, depending on user needs) 120 volt - 20 amp circuits that are hardwired in with NEMA 5-20 R Connectors to plug into cords</td> <td>(10 or more circuits, depending on user needs) 120 volt- 20 amp circuits that are hardwired in with NEMA 5-20 R Connectors to plug into cords</td> </tr> <tr> <td>(6) GFCI receptacles</td> <td>(6) GFCI receptacles</td> </tr> <tr> <td>(22) 20 amp 120 v circuits are available to be used as needed</td> <td>(20) 20 amp 120 v circuits are available to be used as needed</td> </tr> <tr> <td>(1) 30 amp 240 v single phase circuit to be used as needed</td> <td></td> </tr> <tr> <td>(1) 60 amp 240 v 3-phase circuit to be used as needed</td> <td></td> </tr> </tbody> </table>	Panel (A)	Panel (B)	(4 or more circuits, depending on user needs) 120 volt - 20 amp circuits that are hardwired in with NEMA 5-20 R Connectors to plug into cords	(10 or more circuits, depending on user needs) 120 volt- 20 amp circuits that are hardwired in with NEMA 5-20 R Connectors to plug into cords	(6) GFCI receptacles	(6) GFCI receptacles	(22) 20 amp 120 v circuits are available to be used as needed	(20) 20 amp 120 v circuits are available to be used as needed	(1) 30 amp 240 v single phase circuit to be used as needed		(1) 60 amp 240 v 3-phase circuit to be used as needed	
Panel (A)	Panel (B)												
(4 or more circuits, depending on user needs) 120 volt - 20 amp circuits that are hardwired in with NEMA 5-20 R Connectors to plug into cords	(10 or more circuits, depending on user needs) 120 volt- 20 amp circuits that are hardwired in with NEMA 5-20 R Connectors to plug into cords												
(6) GFCI receptacles	(6) GFCI receptacles												
(22) 20 amp 120 v circuits are available to be used as needed	(20) 20 amp 120 v circuits are available to be used as needed												
(1) 30 amp 240 v single phase circuit to be used as needed													
(1) 60 amp 240 v 3-phase circuit to be used as needed													

**GSA Contract Holder**  
Contract # GS-07F-5874P